

NEW XTT 200 DC PULSED TIG INVERTER

Professional Level DC Pulsed TIG Inverter with MMA Function



- 230V Input
- 200A @ 30% Duty Cycle
- Variable Pulse Frequency
- HF Arc Starting
- Digital control
- Optional Foot Control
- Generator Friendly
- Easy Electrode Striking with Arc Force (MMA)
- Easy Electrode Re-striking with Hot Start (MMA)
- Supplied with 3m Earth Lead
- Connections 35-50mm Dinse
- Sturdy Metal Case

- Manufactured to IP23S, ISO/IEC 60974-1, ISO/IEC 60974-6 and RoHS Compliant

Stock Code

XTT200DCP
XTT200DCP-P1

Description

200A DC Pulsed Tig Inverter 230V
Pulsed TIG Inverter with PRO26 Torch Package and Regulator

Technical Information

Parameter	Value
Output Current	10-200 DC
Input Voltage	230V 1P
Input Current Max	18
Duty Cycle	200A @ 30%
Up Slope Function	0-5s
Down Slope Function	0-5s
Pre-flow Function	0-1s
Post Flow Function	3-10s
Pulse Frequency	0.5-100Hz
Fuse Rating	16A
KVA	3.6
Enclosure Protection	IP23S
Dimensions (mm)	376 x 136 x 240
Weight (kg)	8kg

Accessory Information

Stock Code	Description
CKE403	Holder with 3m Lead
CKC403	Earth Cables Clamp Kit x 3m
PRO26-12S1BD19	Pro-Grip Max® TIG 200A Air Cooled Torch 12.5ft
D3595-1-1	TIG Adaptor
E700123	Argon Regulator Single Stage 2 Gauge
WP26AK	TIG Spares Kit in Plastic Case
ERCP19	5 Pin XTT Inverter Plug
XR935H	Everyday Light Reactive Helmet – Black
XTICC	Carry Case (Sold separately)

DC Output

The XTT 200 DCP has a DC output and is suitable for welding alloy, non alloy steels, stainless steel and titanium.

TIG Mode - Materials up to 6mm can be welded with ease.

MMA Mode - Electrodes up to 4.8mm can be used with ease.

TIG Welding

The XTT 200 DCP is suitable for TIG welding steel and stainless steel using the HF start circuit.

Adjustable power pulsing allows reduced heat input and increased penetration.

Generator Friendly

The XTT 200 DCP is able to cope with inputs which fluctuate by +/-15% and can be used with the majority of generators.

The machine is housed in a metal case with integrated carry handle and shoulder strap.

A carry case is available as an optional extra.